

## Doormaster-Smart-PAL-Telephone interface



### Part-No.: 586115

DOORMASTER-SMART-PAL-Telephone interface is used for recording the announcements via similar telephone system in VARIODYN D1 voice alarm system. Up to 4 different call circuits or areas can be addressed using the telephone system. For this purpose 1+ 4 control contacts are available for switching on and/or zone selection.

The connection of telephone interface to VARIODYN D1 takes place via control inputs and audio input of UIM Part. No. 583331.21. 12 V operating voltage can be generated from 24 V emergency power supply with voltage converter Part No. 781336 that is available in the voice alarm system. The voltage converter can be mounted in housing Part No. 788603 on the C-rail in rack.

The programming takes place with MFV post dial, so that the device can also be used from distance.

Operating voltage	12 V DC
Current consumption @ 12 V DC	approx. 100 mA
Contact load relay	24 V DC/0,5 A (relay 1/2)
Ambient temperature	-5 °C ... 45 °C
Mounting	mounting rail
Dimensions	W: 52 mm H: 89 mm D: 57 mm

### Accessories:

586116 Power supply for telephone interface