

Emergency power supply PSU 24 V-2



Part-No.: 581722

Emergency manager for use as emergency power supply of an Voice Alarm – application.

Features:

- Emergency power supply in the 1 HU enclosure
- Outputs for control devices such as DOM or Comprio net
- 8 individually fused high power outputs for output amplifiers, each with 30A max.
- Authorisation pursuant to EN 54-4(A2)
- LED displays and display for status reports
- Potential-free contacts for the transmission of alarm messages
- Battery capacity up to a total of 320 Ah
- Maximum output 186 A

Rated voltage	230 V AC
Ambient temperature	-5 °C ... 40 °C
Storage temperature	-40 °C ... 85 °C
Weight	approx. 5,2 kg
Dimensions	W: 483 mm H: 45 mm D: 328 mm



2 batteries of the same kind are required for each emergency power supply.

Accessories:

581730	Battery for emergency power supply 12 V / 105 Ah
581731	Battery for emergency power supply 12 V / 150 Ah