

## Emergency power supply PSU 24 V-4




**Part-No.: 581723**

Emergency manager for use as emergency power supply of an Voice Alarm – application.

### Features:

- Emergency power supply in the 2 HU enclosure
- Outputs for control devices such as DOM or Comprio net
- 1 individually fused high power outputs for output amplifiers (12 outputs in total but one output cannot be used)
- Authorisation pursuant to EN 54-4(A2)
- LED displays and display for status reports
- Potential-free contacts for the transmission of alarm messages
- Battery capacity up to a total of 640 Ah
- Maximum output current in case of emergency power situation 372 A

Rated voltage	230 V AC
Ambient temperature	-5 °C ... 40 °C
Storage temperature	-40 °C ... 85 °C
Weight	approx. 8,8 kg
Dimensions	W: 483 mm H: 89 mm D: 328 mm

 Up to 2 x 2 batteries of the same kind are required for each emergency power supply.

### Accessories:

581730	Battery for emergency power supply 12 V / 105 Ah
581731	Battery for emergency power supply 12 V / 150 Ah